

CI865

System 800xA hardware selector



The CI865 module is the AC 800M system's communication interface for Satt ControlNet and bridges different bus standards used on AC 800M and Satt ControlNet. The CI865 module makes it possible to use older Satt I/O system (Rack I/O and Series 200 I/O) with the AC 800M controller platform, but it cannot be used as a general ControlNet interface. CI865 cannot be used in a High Integrity controller.

Features and benefits

- Satt 19 inch rack I/O, a rack-based I/O system, can be connected to AC 800M using the CI865 interface module
- CI865 supports online replacement (Hot Swap), and does not require any configuration before installation
- The CI865 unit handles I/O scanning of up to 31 distributed I/O systems

General info	
Protocol	ABB's Satt I/O
Article number	3BSE040795R1
Master or slave	Master
Transmission speed	-
Line redundancy	No
Module redundancy	No
Hot Swap	Yes
Used together with HI Controller	No

Detailed data	
Max units on CEX bus	4
Connector	BNC
24 V consumption typ.	typ 120 mA

Environmental and certification	
Temperature, Operating	55 °C
Protection class	IP20 according to EN60529, IEC 529
CE- marking	Yes
RoHS compliance	EN 50581:2012
WEEE compliance	DIRECTIVE/2012/19/EU

Dimensions	
Height	185 mm (7.3 in.)
Width	59 mm (2.3 in.)
Depth	127.5 mm (5.0 in.)
Weight (including base)	700 g (1.5 lbs)

www.abb.com/800xA
www.abb.com/controlsystems

800xA is a registered or pending trademark of ABB. All rights to other trademarks reside with their respective owners.

We reserve the right to make technical changes to the products or modify the contents of this document without prior notice. With regard to purchase orders, the agreed particulars shall prevail. ABB does not assume any responsibility for any errors or incomplete information in this document.

We reserve all rights to this document and the items and images it contains. The reproduction, disclosure to third parties or the use of the content of this document – including parts thereof – are prohibited without ABB's prior written permission.

Copyright© 2018 ABB All rights reserved