

# CI873

## System 800xA hardware selector



The CI873 is an AC 800M communication interface that connects to external Ethernet devices using the EtherNet/IP protocol. The TP867 Baseplate has two RJ45 Ethernet connectors, but only the CH1 connector that supports 100Mbps is used. The CI873 expansion unit contains the CEX-Bus logic, a communication unit, and a DC/DC converter that supplies the required voltage from +24 V supply through the CEX-Bus. The new S200CI873IoHwlib adds support for the S200 I/O adaptor 200-AENTR to be used with CI873.

This new adaptor gives a simple and cost effective upgrade path for directly connected S200 I/O on SattCon 200, SattLine 200, Advant Controller 210, Advant Controller 250 and AC 800C. The 200-AENTR has two Ethernet ports with an in-built switch, which means that the adaptors can be daisy-chained to the CI873 using cross-wired Ethernet-cables without the need for external switches.

### Features and benefits

- Supports connection for S200 I/O via 200-AENTR adaptor
- Supports Ethernet/IP and Device Net protocols

General info	
Protocol	EtherNet IP / DeviceNet
Article number	3BSE056899R1
Master or slave	Master
Transmission speed	10/100 Mbit/s
Line redundancy	No
Module redundancy	Yes
Hot Swap	Yes
Used together with HI Controller	Yes

Detailed data	
Max units on CEX bus	4
Connector	RJ-45 female (8-pin)
24V consumption typ.	typ 160 mA

**Environmental and certification**

Temperature, Operating	55 °C
Protection class	IP20 according to EN60529, IEC 529
CE-marking	Yes
Marine certificates	ABS, BV, DNV-GL, LR
RoHS compliance	EN 50581:2012

**Dimensions**

Height	185 mm (7.3 in.)
Width	59 mm (2.3 in.)
Depth	127.5 mm (5.0 in.)
Weight (including base)	700 g (1.5 lbs)

---

[www.abb.com/800xA](http://www.abb.com/800xA)  
[www.abb.com/controlsystems](http://www.abb.com/controlsystems)

---

800xA is a registered or pending trademark of ABB. All rights to other trademarks reside with their respective owners.

We reserve the right to make technical changes to the products or modify the contents of this document without prior notice. With regard to purchase orders, the agreed particulars shall prevail. ABB does not assume any responsibility for any errors or incomplete information in this document.

We reserve all rights to this document and the items and images it contains. The reproduction, disclosure to third parties or the use of the content of this document – including parts thereof – are prohibited without ABB's prior written permission.

Copyright© 2017 ABB All rights reserved